

Updating the Handheld OS (Tutorial A12)

http://www.atomiclearning.com/k12/en/movie/85844/play_window?type=Tutorial&sid=2410

[00:00:00.00]

It's important that you make sure your TI-Nspire or TI-Nspire CAS handheld is running the current operating system,

[00:00:07.00]

and that you also have your TI-Nspire Software up-to-date. Updating the OS will keep your saved documents, but it's

[00:00:15.00]

a good idea to back up important documents to your computer regularly. If you haven't done so, open the TI-Nspire computer

[00:00:23.00]

software. I'll plug my handheld into the computer's USB port and turn it on. Now make sure you have an active Internet

[00:00:32.00]

connection on your computer, and then we can click on the Content tab at the very top, and then on the left side

[00:00:39.00]

of the window under Resources, we can click and select our Connected Handheld. Next we can click on the Help menu

[00:00:48.00]

and you'll see that you have the option to check for software updates here, as well as the Handheld OS updates. Be sure

[00:00:55.00]

that you do both periodically. In this case, I'll choose Check for Handheld OS Update. You'll see a dialog box appear

[00:01:03.00]

after a few seconds either letting you know that your handheld is up-to-date or prompting you to install the current OS.

[00:01:10.00]

If the OS is out-of-date, you have a few options before you update it. The first check box will install the OS

TI-Nspire™ Handheld Script

[00:01:17.00]

on the current, active handheld. The second check box will save a copy of the OS to a location on your computer's

[00:01:24.00]

hard drive. You can also use the Browse button to specify this location. The third check box will automatically check

[00:01:32.00]

for updates. Once you've got those settings the way you want them, you can click Continue. Next you'll see the

[00:01:40.00]

License Agreement dialog box. I'll click the top Radio button to accept the terms of the License Agreement and

[00:01:47.00]

then click Continue. Once the update is complete, the handheld will display a message letting you know that it's safe

[00:01:52.00]

to unplug and reboot the device.

[00:01:57.00]